(1)



Move the downloaded MCU and CPU Firmware to the computer desktop.



Unzip the downloaded MCU and CPU Firmware and install it on the computer desktop.



파일 홈 공유 보기						
	달라내기 경로 복사 이문 바로 가기 붙여넣기 위치	동 복사 삭제 I * 위치 * ·	<b>미</b> 름 바꾸기	▲ 세 항목 • 1 빠른 연결 • 새 폴더	↓ 월 일기 ▼   속성 ♪ 편집   ▼ ↓ 히스토리	문 모두 선 응 선택 인 응 선택 영 용 성 명 명 명 명 명 명 명 명 명 명 명 명 명 명 명 명 명 명
클립보드		구성		새로 만들기	열기	선택
🗸 📙 📼						
← → ∨ ↑ 📑 > 내 PC > 바탕 화면 > M_NAMSUNG_V0.62_DMCPA79BT						✓ Ŭ M
	이르	^	4	저하 날짜	으형 그	71
★ 바로 가기 № Documents ► 사진		IAMSUNG.FIR IAMSUNG_MCU		)19-10-25 오후 1:02 )19-10-24 오후 3:58	FIR 파일 ALZip BIN File	16,384KB 71KB
3 SDHC (E:)						
, S 내 PC	2					
🔚 3D 개체	19					
🛅 Documents	•					
🐌 다운로드						
🔚 동영상						
┣ 바탕 화면						

Copy the extracted MCU and CPU Firmware to the USB Thumb Drive.





#### Insert USB Thumb Drive with Update Firmware into DMCPA79BT's USB Port.





NO FILE Text is displayed while checking the Update Firmware on the USB.

(6)



NO FILE Text disappears when File Check of USB Thumb Drive is completed



Move to Setting Mode Screen and press Upgrade-CPU MCU Text for over 3 seconds.





#### Start CPU and MCU Firmware Update







Power off / on automatically when MCU and CPU firmware is completed.

### (10)



Check if the updated MCU and CPU firmware version is V0.62 (NS) - V1.1303 (A).